


1451C/CLR

TROUBLESHOOTING

GUIDE



CTX

The Monitor Specialists

EDITION 1
July 1995

CONTENTS

1.0 IMPORTANT NOTICE & INTRODUCTION.....	1
2.0 GENERAL MAINTENANCE PROCEDURE	2
3.0 FUNCTION BLOCK DIAGRAM BLOCK.....	3
4.0 TIMING MODE	4
5.0 ADJUSTMENT.....	6
6.0 TROUBLESHOOTING	8
6.1 MAIN TROUBLESHOOTING ROUTINE.....	8
6.2 POWER SAVING CIRCUIT TROUBLESHOOTING ROUTINE.....	9
6.3 POWER SUPPLY CIRCUIT TROUBLESHOOTING ROUTINE	11
6.4 VIDEO CIRCUIT TROUBLESHOOTING ROUTINE.....	13
6.5 DEFLECTION CIRCUIT TROUBLESHOOTING ROUTINE	15
6.5.1 Horizontal Deflection Circuit.....	15
No Raster	15
H-Asynchronous	16
Linearity	17
Out of phase	18
Width Abnormal	18
6.5.2 Vertical Deflection Circuit	19
No vertical scan	19
Side pin distortion	20
V-Asynchronous	21
Vertical position	21
Vertical Size.....	22
7.0 IC CONFIGURATION.....	26
8.0 LAYOUT FOR MAIN COMPONENTS AND ADJUSTED	28
9.0 CIRCUIT DIAGRAM	28
10.0 SPARE PARTS LIST & TRANSISTOR PINS ARRANGEMENT	29
11.0 CRT CONTRAST LIST	30

Copyright ©1995 by Chutnex Electronic Co., Ltd.

The CTX TROUBLESHOOTING GUIDE is published by Chuntex Electronic Co., Ltd.

All rights reserved. No part of this manual may be used, copied, reproduced, or transmitted in any form or by any means for any purpose without the express written permission of the publisher.

The publisher has been trying its best to make this publication perfect, and in this manner takes no responsibility for the use of any of the materials or methods described in this manual, or for the products thereof. Neither will the publisher be responsible for any damages caused by misuse or misquotation.

Information in this manual is subject to change by the publisher without any notice in advance.

CTX is a registered trademark of Chuntex Electronic Co., Ltd.

1.0 IMPORTANT NOTICE & INTRODUCTION

IMPORTANT NOTICE

Please read before attempting service

1. While the monitor is in operation, do not attempt to connect or disconnect any wires.
2. Make sure the power cord is disconnected before replacing any parts in the monitor.
3. When the power is on, do not attempt to short any portion of the circuit. This shorting may cause damage to the transistors in the monitor.
4. When servicing the H.V. area, be certain that the C.R.T anode is safely discharged before removing the anode cap.
5. Caution must be exercised when servicing this monitor.

INTRODUCTION


Enhanced repair capabilities

This troubleshooting guide is edited for model 1451C/CLR when service is necessary. There are four primary parts included in this troubleshooting guide which offer the easiest way to locate problem points and repair the machine to the best possible condition.


1. The Adjustment section offers the adjustable method, steps and all data of the factory's initial settings which can make the machine get the best performance at that time. By the way, before adjusting, the machine must be warmed up for at least 10 minutes and the CRT face must be in an eastward direction.
2. The Troubleshooting section has four main parts including: power supply, power saving, CRT, deflection & video circuit. Each offers fast repair routine and the IC, transistor voltage records against all specified signal modes. These voltage readings are measured with a HP 34401A multimeter with input impedance $10\text{M}\Omega$ (0.1V ~ 1000V range) and waveforms shown on circuit schematics are measured by a Tektronix TDS 520 digital oscilloscope, the monitor receives VGA-400 full white square pattern.

3. The CRT contrast list offers repairmen / technicians the contrast data when CRT replacement is necessary from a different type of CRT.
4. The Spare parts list offers the CTX part number (P/N) which is used frequently by repairmen / technicians. For details please refer to the service guide or service manual. If there is any engineering change regarding this model, CTX will issue the updated information by a non-periodical Technical Bulletin.

2.0 GENERAL MAINTENANCE PROCEDURE



3.0 FUNCTION BLOCK DIAGRAM BLOCK



4.0 TIMING MODE

NAME	VGA-350		VGA-400		VGA-480		SVGA I		SVGA II	
PIXEL RATE	25.2 MHZ		25.2 MHZ		25.2 MHZ		36 MHZ		40 MHZ	
Fh	31.5 KHZ		31.5 KHZ		31.5 KHZ		35.156KHZ		37.879 KHZ	
Fv	70 HZ		70 HZ		60 HZ		56.250HZ		60.3165 HZ	
INTERLACE MODE	NO		NO		NO		NO		NO	
OUTPUT	ANALOG		ANALOG		ANALOG		ANALOG		ANALOG	
FULL SCALE Vpp	1,000		1,000		1,000		1,000		1,000	
SYNC ON R/G/B	NO		NO		NO		NO		NO	
CONTROL BITS	0000 0000		0000 0000		0000 0000		0000 0000		0000 0000	
UNIT	PIXEL	ms/us	PIXEL	ms/us	PIXEL	ms/us	PIXEL	ms/us	PIXEL	ms/us
FRAME BORDER-H		us		us		us		us		us
FRAME BORDER-V		ms		ms		ms		ms		ms
H TOTAL	800	31.78 us	800	31.78 us	800	31.78 us	1024	28.444 us	1056	26.4 us
H DISPLAY	641	25.42 us	641	25.42 us	641	25.42 us	800	2.222 us	800	20.0 us
H REAR PORCH	48	1.91 us	48	1.91 us	48	1.91 us	128	3.556 us	88	2.2 us
H SYNC WIDTH	96	3.81 us	96	3.81 us	96	3.81 us	72	2.0 us	128	3.2 us
H SYNC POLARITY	+		-		-		-		+	
VTOTAL	450	14.27 ms	450	14.27 ms	525	16.68 ms	625	17.778 ms	628	16.579 ms
V DISPLAY	350	11.12 ms	400	12.71 ms	480	15.25 ms	600	17.067 ms	600	15.840 ms
V REAR PORCH	60	1.91 ms	35	1.11 ms	33	1.05 ms	22	0.626 ms	23	0.607 ms
V SYNC WIDTH	2	0.06 ms	2	0.06 ms	2	0.06 ms	2	0.057 ms	4	0.108 ms
V SYNC POLARITY	-		+		-		-		+	
EQUALIZATION ?	NO		NO		NO		NO		NO	
SERRATION ?	NO		NO		NO		NO		NO	
COMP SYNC POLARITY	-		-		-		-		-	

NAME	SVGA III		VESA-480		8514A		8514NI	
PIXEL RATE	50 MHZ		31.5 MHZ		44.9 MHZ		65 MHZ	
Fh	48.077 KHZ		37.860 KHZ		35.5 KHZ		48.363 KHZ	
Fv	72.187 HZ		72.809 HZ		87 HZ		60 HZ	
INTERLACE MODE	NO		NO		VIDEO		NO	
OUTPUT	ANALOG		ANALOG		ANALOG		ANALOG	
FULL SCALE Vpp	1,000		1,000		1,000		1,000	
SYNC ON R/G/B	NO		NO		NO		NO	
CONTROL BITS	0000 0000		0000 0000		0000 0000		0000 0000	
UNIT	PIXEL	ms/us	PIXEL	ms/us	PIXEL	ms/us	PIXEL	ms/us
FRAME BORDER-H		us		us		us		us
FRAME BORDER-V		ms		ms		ms		ms
H TOTAL	1040	20.80 us	832	26.413 us	1264	28.10 us	1344	20.677 us
H DISPLAY	800	16.0 us	640	20.317 us	1024	22.80 us	1024	15.754 us
H REAR PORCH	64	1.28 us	128	4.063 us	52	1.15 us	160	2.462 us
H SYNC WIDTH	120	2.40 us	40	1.270 us	176	3.91 us	136	2.092 us
H SYNC POLARITY	+		-		+		-	
VTOTAL	666	13.853 ms	520	13.735 ms	408	11.50 ms	806	16.667 ms
V DISPLAY	600	12.480 ms	480	12.678 ms	384	10.80 ms	768	15.880 ms
V REAR PORCH	23	0.478 ms	28	0.740 ms	20	0.56 ms	29	0.600 ms
V SYNC WIDTH	6	0.125 ms	3	0.079 ms	4	0.11 ms	6	0.124 ms
V SYNC POLARITY	+		-		+		-	
EQUALIZATION ?	NO		NO		NO		NO	
SERRATION ?	NO		NO		NO		NO	
COMP SYNC POLARITY	-		-		-		-	

5.0 ADJUSTMENT

5.1 1451C ADJUSTMENT

- voltage adjustment: VR101/SVGA II

1. Use SVGA II timing for input signal.
2. Attach the multimeter (with a DC voltage range of 200V) between cathod of D111 and GND, and adjust VR101 to get $85V \pm 0.2V$.

- H-F/V adjustment: VR301/SVGA (37.8KHz)

Measure the DC voltage between TP3 and GND, and adjust VR301 to get $9V \pm 0.05V$.

- Hi-voltage adjustment: VR501 / SVGA II

- a. Turn the power switch off before attaching multimeter with a high voltage probe by a factor 1000:1 between CRT anode and GND.
- b. Adjust VR501 to make sure the measurement readings are $24V \pm 0.5V$ (ie CRT anode voltage is $24KV \pm 0.5KV$).

- Horizontal hold adjustment: VR201/SVGA

Connect TP1 to GND and adjust VR201 to get picture stand or scroll toward left or right slowly when input is SVGA II.

- H-PHASE adjustment: EXT VR(VR202) / VGA-480

Adjust EXTERNAL H-PHASE to shift picture to the center of screen.

- V-line adjustment: VR801/VGA-480

First adjust V-CENTER EXTERNAL VR to make picture to the V-center of the screen, and then adjust VR801 to correct the V-linearity of cross-hatch pattern.

- H-WIDTH adjustment: VR401/VGA-480

- a. Adjust EXTERNAL H-WIDTH VR to get picture width just full screen.
- b. Adjust EXTERNAL H-WIDTH VR to get the horizontal width of every mode is $252 \pm 5mm$.

- V-SIZE adjustment: EXT VR

Adjust EXTERNAL V-SIZE VR to get the vertical size of every mode is $189 \pm 7mm$.

- PINCUSHION adjustment: VR803/VGA-480

Adjust VR803 to parallel the picture's right & left edge each other.

- FOCUS adjustment: FOCUS VR/VGA-480

Adjust FOCUS VR on the FBT to attain a balanced focus for all points on the screen.

- White balance adjustment:

- a. Pre adj. & brightness settings (Before adjusting, CRT must be degaussed.)
 - (1) Set the VR601,602,603,604,605,606 on mechanical center, and the Brightness VR to the click point, the Contrast VR to Max.
 - (2) Operating on VGA-480 mosaic pattern and adjust the SCREEN VR to set the raster luminance between 2 ~ 3FL, are measure by color Analyzer.
 - (3) Adjust VR604,605,606 (BIAS VR) to make C.I.E. coordinates value as $x=0.281 \pm 0.01$, $y=0.311 \pm 0.01$ are measured by color analyzer.
 - (4) Change timing to VGA-400 color bar pattern, correct SCREEN VR which on the FBT to make raster brightness disappear and the "1" row of color bar pattern (as below figure) visible obscurely.
 - (5) Operating on VGA-480 mosaic pattern again, check the Brightness of Mosaic pattern is between 67 ~ 70FL. If the brightness isn't net, adjust VR603, to make it and return to step(2).

		R+B			B+G		R+G		
Brightness		BRIGHT BLUE	BRIGHT RED	BRIGHT PURPLE	GREEN	BLUE + GREEN	RED + YELLOW	WHITE	
	15								7
	14								6
	13								5
reduce	12								4
	11								3
	10								2
	9								1
	8								0

→visible
→visible
obscurely

b. White balance fine regulation:

- (1) Receive VGA-480 timing, full white square pattern.
- (2) Adjust BRIT. VR. to MIN., CONT. VR. to MAX..
- (3) Adjust VR601,602,603 to make $x=0.281 \pm 0.01$, $y=0.311 \pm 0.01$, are measured by color Analyzer.
- (4) Change the BRIT. VR to the click point and the CONT. VR between 1 ~ 2FL, then adjust VR604,605,606 (BIAS VR) to get $X=0.281 \pm 0.005$, $Y=0.311 \pm 0.005$, are measured by color Analyzer.
- (5) If the white balance is not met, repeat step (2) ~ (4).

• ADJUSTMENT FOR CONVERGENCE

- (1) Produce a magenta crosshatch on the display.
- (2) Adjust the focus for the best overall focus on the screen.
- (3) Also adjust the brightness to the desired condition.
- (4) Vertical red and blue lines are converged by varying the angle between the two tabs of the 4 pole magnets on the PCM assembly. (See diagram below)
- (5) Horizontal red and blue lines are converged by moving the two tabs at the same time keeping the angle between them constant.
- (6) Produce a white crosshatch pattern on the display.
- (7) Vertical green and magenta lines are converged by varying the angle between the two tabs of the 6-pole magnets.
- (8) Horizontal green and magenta lines are converged by moving the two tabs at the same time keeping the angle between them constant.

DEFLECTION YOKE


6-POLE
CONVERGENCE MAGNETS
4-POLE
CONVERGENCE MAGNETS
PURITY MAGNETS

PCM: PURITY CONVERGENCE MAGNET


Note: Please don't adjust the purity magnets when service occurs.

6.0 TROUBLESHOOTING

6.1 MAIN TROUBLESHOOTING ROUTINE



6.2 POWER SAVING CIRCUIT TROUBLESHOOTING ROUTINE



VOLTAGE MEASURED RECORD

TEST CONDITIONS: AC LINE IN:110V,220V/60Hz

TIMING : VGA-350

PATTERN: CROSS HATCH

STATUS : NORMAL


VOLTAGE MEASURED RECORD

Unit: Volt

TR	Q110 (B772)			Q111 (2SC945)			Q114 (2SD882)		
PIN	B	C	E	B	C	E	B	C	E
MODE									
NORMAL	22.64	23.32	23.35	0.73	0.03	GND	12.99	15.04	12.34
POWER SAVING	27.36	1.19	27.34	0.01	27.38	GND	1.17	14.14	0.63

TR	Q115 (2SC945)			Q116 (2SA733)			IC301 (8045)		
PIN	B	C	E	B	C	E	14	15	
MODE							(PM1)	(PM2)	
NORMAL	6.79	12.99	6.16	9.34	0.33	6.3	3.12	3.12	
POWER SAVING	0.35	1.17	0.63	3.03	3.65	3.73	0.0	0.0	

6.3 POWER SUPPLY CIRCUIT TROUBLESHOOTING ROUTINE



VOLTAGE MEASURED RECORD

TEST CONDITIONS: AC LINE IN:110V,220V/60Hz

TIMING : VGA-350

PATTERN: CROSS HATCH

STATUS : NORMAL


VOLTAGE MEASURED RECORD

Unit: Volt

TR	Q101 (2SK1118)		
PIN	G	D	S
MODE			
110V	3.2	143.0	0.07
220V	1.25	302.65	0.03

IC	IC101 (3842N)							
PIN	1	2	3	4	5	6	7	8
MODE								
110V	2.89	2.48	0.22	0.48	GND	3.82	16.88	4.98
220V	3.72	2.47	0.35	0.52	GND	1.75	16.84	4.98

6.4 VIDEO CIRCUIT TROUBLESHOOTING ROUTINE



The following voltage records was measured with cross-hatch pattern.

Transistor & Integration circuit


TR	Q601 (PH2369)			Q602 (PH2369)			Q603 (PH2369)		
PIN	B	C	E	B	C	E	B	C	E
MODE									
VGA-350	1.66	9.44	1.61	1.66	9.45	1.61	1.67	9.43	1.60


TR	Q604 (2SC3788)			Q605 (2SC3788)			Q606 (2SC3788)		
PIN	B	C	E	B	C	E	B	C	E
MODE									
VGA-350	10.06	74.22	9.44	10.06	74.24	9.45	10.07	74.43	9.43


IC	IC601 (M51387P)								
PIN	2	3	4	6	7	8	10	11	12
MODE									
VGA-350	12.27	2.74	5.0	12.27	2.73	5.03	12.27	2.74	5.23
PIN	14	15	16	17	18	19	20	21	22
MODE									
VGA-350	6.76	0.47	3.34	GND	GND	3.51	4.28	1.67	GND
PIN	23	24	25	26	27	28	29	30	
MODE									
VGA-350	3.5	4.29	1.66	GND	3.47	4.27	1.65	12.27	



6.5 DEFLECTION CIRCUIT TROUBLESHOOTING ROUTINE

6.5.1 Horizontal Deflection Circuit


No Raster


H-Asynchronous



Linearity

Out of phaseWidth Abnormal


6.5.2 Vertical Deflection Circuit

No vertical scan

Side pin distortion

V-AsynchronousVertical position

REMARK: fH horizontal frequency

Vertical Size

The following voltage records were measured with cross-hatch pattern.

Transistor

Unit:volt

TR	Q201 (2SC733)			Q202 (2SA733)			Q301 (2SC945)		
PIN	B	C	E	B	C	E	B	C	E
MODE									
8514NI	11.35	0.0	11.61	1.93	GND	2.58	5.08	23.41	4.67
SVGA II	8.82	GND	9.44	1.95	GND	2.60	5.08	23.44	4.66
8514A	8.29	GND	8.91	2.19	GND	2.82	5.07	23.41	4.65
VGA-350	7.38	GND	8.01	2.32	GND	2.96	5.08	23.21	4.68

TR	Q401 (BU2508AF)			Q402 (2SK2134)			Q403 (2SD313)		
PIN	G	D	S	G	D	S	B	C	E
MODE									
8514NI	-0.25	148.30	GND	22.46	48.3	21.58	0.55	15.83	0.0
SVGA II	-0.32	112.28	GND	12.55	21.74	11.89	0.54	11.82	GND
8514A	-0.33	104.47	GND	12.38	31.6	11.72	0.53	14.56	GND
VGA-350	-0.33	91.22	GND	21.80	11.03	10.99	0.53	10.96	GND

TR	Q404 (2SA733)			Q405 (BF423)			Q406 (2SC2688)		
PIN	B	C	E	B	C	E	B	C	E
MODE									
8514NI	15.75	0.55	15.83	15.83	147.95	5.17	148.58	76.29	GND
SVGA II	11.62	0.57	11.82	11.82	11.49	3.75	112.13	74.08	GND
8514A	14.52	0.53	14.44	14.44	103.42	3.28	104.05	74.08	GND
VGA-350	10.88	0.53	10.96	10.96	90.35	2.87	90.97	75.83	GND

TR	Q407 (2SK2134)			Q408 (BF423)			Q410 (BF423)		
PIN	G	D	S	B	C	E	B	C	E
MODE									
8514NI	22.21	47.62	21.69	1.58	-1.97	2.34	77.29	21.5	78.25
SVGA II	21.91	11.71	11.61	1.53	-2.07	2.28	57.88	11.24	58.75
8514A	24.88	14.72	14.70	1.54	-3.77	2.29	53.68	14.68	54.53
VGA-350	21.28	11.0	10.95	1.50	-2.55	2.25	46.88	10.82	47.7

TR	Q411 (BF422)			Q412 (2SA733)			Q501 (2SK2134)		
PIN	B	C	E	B	C	E	G	D	S
MODE									
8514NI	9.75	29.66	9.13	11.08	GND	11.63	4.0	59.71	0.12
SVGA II	7.85	29.83	7.22	9.02	GND	9.66	2.85	59.86	0.08
8514A	7.46	28.80	6.83	8.51	GND	9.15	2.56	59.92	0.07
VGA-350	6.8	24.77	6.16	7.69	GND	8.33	2.09	59.96	0.05

TR	Q502 (FB422)			Q503 (2SC945)			Q801 (2SC945)		
PIN	B	C	E	B	C	E	B	C	E
MODE									
8514NI	2.96	107.22	2.43	0.67	0.01	GND	2.86	6.02	2.34
SVGA II	2.22	82.19	1.70	0.67	0.01	GND	2.86	6.03	2.34
8514A	2.06	76.69	1.54	0.67	0.01	GND	3.99	5.99	3.44
VGA-350	1.8	67.85	1.28	0.67	0.01	GND	3.83	6.02	3.30

TR	Q802 (2SC945)			Q803 (2SA733)			Q804 (2SC945)		
PIN	B	C	E	B	C	E	B	C	E
MODE									
8514NI	11.3	23.54	11.4	10.75	GND	11.4	6.14	18.17	5.54
SVGA II	11.26	23.46	11.37	10.72	GND	11.37	6.13	18.16	5.52
8514A	11.24	23.41	11.34	10.61	GND	11.34	6.14	18.16	5.55
VGA-350	11.16	23.23	11.24	10.61	GND	11.25	6.14	18.16	5.55

TR	Q805 (2SA733)			Q806 (2SA733)			Q808 (2SA733)		
PIN	B	C	E	B	C	E	B	C	E
MODE									
8514NI	6.15	15.02	5.53	4.37	GND	5.01	2.18	GND	2.86
SVGA II	6.14	15.42	5.52	4.35	GND	5.0	2.18	GND	2.87
8514A	6.17	14.01	5.55	4.36	GND	5.01	3.28	GND	3.96
VGA-350	6.17	14.14	5.55	4.37	GND	5	3.15	GND	3.83

TR	Q809 (2SA733)			Q810 (2SC945)			Q811 (2SA733)		
PIN	B	C	E	B	C	E	B	C	E
MODE									
8514NI	5.2	GND	5.71	0.73	0.32	GND	23.43	12.89	23.43
SVGA II	3.76	GND	4.32	0.73	0.32	GND	23.47	12.92	23.46
8514A	3.29	GND	3.85	0.72	0.41	GND	23.42	12.87	23.41
VGA-350	2.87	GND	3.44	0.72	0.36	GND	23.23	12.63	23.24

Integration Circuit

IC	IC201 (7851)									
PIN	1	2	3	4	5	6	7	8	9	10
MODE										
VGA-350	7.94	8.42	8.6	-0.3	4.22	3.57	6.81	6.59	6.4	12.31
PIN	11	12	13	14	15	16	17	18	19	20
MODE										
VGA-350	7.09	4.36	0.0	GND	NG	3.60	0.21	3.19	6.04	12.32

Integration Circuit


IC	IC301 (7851)						
PIN	1	2	3	4	5	6	7
MODE							
8514NI	2.33	2.41	3.08	3.36	0.47	0.04	0.17
SVGA II	2.33	2.41	0.57	0.2	0.6	0.03	11.46
8514A	2.33	2.41	0.63	0.23	0.67	0.07	11.45
VGA-350	2.33	2.41	0.57	3.38	0.59	0.02	11.45
PIN	8	9	10	11	12	13	14
MODE							
8514NI	0.09	0.14	1.43	3.48	GND	0.7	3.12
SVGA II	0.08	0.14	1.44	3.47	GND	0.77	3.12
8514A	12.31	0.14	2.86	2.73	GND	0.75	3.12
VGA-350	12.31	11.39	2.23	3.23	GND	0.6	3.12
PIN	15	16	17	18	19	20	21
MODE							
8514NI	3.12	0.74	2.29	11.06	2.1	2.07	2.07
SVGA II	3.12	0.72	2.76	7.01	2.13	2.09	2.1
8514A	3.1	0.63	2.9	6.23	3.08	3.07	3.08
VGA-350	3.11	0.63	3.16	5.01	2.95	2.94	2.95
PIN	22	23	24	25	26	27	28
MODE							
8514NI	8.83	8.79	12.3	2.06	0.01	NC	5.08
SVGA II	7.19	0.01	12.31	2.1	7.14	NC	5.08
8514A	6.57	6.53	12.31	0.01	6.52	0.63	5.08
VGA-350	6.10	6.07	12.30	2.94	6.07	NC	5.08

IC	IC501 (UC3843)							
PIN	1	2	3	4	5	6	7	8
MODE								
8514NI	3.48	2.49	0.12	0.19	GND	4.06	12.32	4.99
SVGA II	3.34	2.49	0.08	0.3	GND	2.89	12.32	5.0
8514A	3.26	2.49	0.07	0.34	GND	2.57	12.32	5.0
VGA-350	3.13	2.49	0.05	0.41	GND	2.11	12.32	5.0


IC	IC801 (LA7837)												
PIN	1	2	3	4	5	6	7	8	9	10	11	12	13
MODE													
VGA-350	11.7	3.61	5.85	6.01	11.13	5.44	5.95	23.16	1.36	1.47	GND	12.85	23.0

7.0 IC CONFIGURATION


1. IC101 (3842)




2. IC501 (3843)




3. IC301 (WT8045)




4. IC601(M51387P)



5. IC801(LA7837)



6. IC201(LA7851)



8.0 LAYOUT FOR MAIN COMPONENTS AND ADJUSTED

9.0 CIRCUIT DIAGRAM

10.0 SPARE PARTS LIST & TRANSISTOR PINS ARRANGEMENT

MAIN BOARD REV.B					
ITEM	PART NO.	DESCRIPTION	LOCATION	PIN'S ARRANGE	REMARK
1	17A06-150H	3842/17384	IC101		
2	17A06-140H	LA7851	IC201		
3	17A01-002M	8045	IC301		
4	17A06-190H	3843	IC501		
5	17A06-110H	LA7837	IC801		
6	15D67-F000	600V 4A PBL405	BD101		
7	49FB2-0A0B	250V 3.15A	F101		
8	14K22-0908	2SK2141	Q101	GDS	
9	14A92-021B	2SA733	Q102,Q116,Q201,Q202, Q404,Q412,Q803,Q806, Q808,Q809,Q811	ECB	
10	14A92-061E	BF423	Q405,Q408,Q410	ECB	
11	14C92-011E	BF422	Q411,Q502	ECB	
12	14C92-111B	2SC945	Q111,Q115,Q301,Q503, Q801,Q802,Q804,Q805, Q810	ECB	
13	14B26-030B	2SB772	Q110	ECB	
14	14C26-040B	2SC2688	Q406	ECB	
15	14K22-110B	2SK2134	Q402,Q407,Q501	GDS	
16	14D22-110C	2SD313	Q403	BCE	
17	14D26-0108	2SD882	Q114	ECB	
18	14C3P-140P	BU2508DF	Q401	BCE	
19	15S3C-601F	1500V 3A 3TH41	D402		
20	47F13-0420	FBT	T401		

CRT BOARD REV.B					
ITEM	PART NO.	DESCRIPTION	LOCATION	PIN'S ARRANGE	REMARK
1	17A04-020H	M51387P	IC601		
2	14C92-031E	PH2369	Q601,Q602,Q603	CBE	
3	14A26-100C	2SC3788	Q604,Q605,Q606	ECB	

11.0 CRT CONTRAST LIST

THE 1451C SERIES MONITOR HAVE SEVERAL KINDS OF CRT AS LIST.

THE DIFFERENT PARTS BETWEEN THEM HAVE BEEN SHOWN IN FOLLOW.





LR

PARTS	TYPE	HITACHI 20H14-026A	CHUNGHWA 20H14-106B	PANASONIC 20H14-116C	TOSHIBA 20H14-1561	SAMSUNG 20H14-276A
R330		24K 1/8W 23A11-243M	27K 1/8W 23A11-273M	24K 1/8W 23A11-243M	27K 1/8W 23A11-273M	24K 1/8W 23A11-243M
R433		15K 1/4W 22225-153M	16K 1/4W 22225-163M	15K 1/4W 22225-153M	15K 1/4W 22225-153M	15K 1/4W 22225-153M
R434		4.3K 1/4W 22225-432M	5.1K 1/4W 22225-512M	4.3K 1/4W 22225-432M	5.1K 1/4W 22225-512M	5.1K 1/4W 22225-512M
R508		30K 1/4W 22225-303M	30K 1/4W 22225-303M	30K 1/4W 22225-303M	30K 1/4W 22225-303M	36K 1/4W 22225-363M
R805		110K 1/4W 22225-114M	110K 1/4W 22225-114M	100K 1/4W 22225-104M	110K 1/4W 22225-114M	110K 1/4W 22225-114M
R807		39K 1/8W 22215-393M	39K 1/8W 22215-393M	39K 1/8W 22215-393M	39K 1/8W 22215-393M	39K 1/8W 22215-393M
R808		4.7K 1/8W 22215-472M	4.7K 1/8W 22215-472M	4.7K 1/8W 22215-472M	4.7K 1/8W 22215-472M	4.7K 1/8W 22215-472M
C823		0.01 μ 39146-103R	0.01 μ 39146-103R	0.01 μ 39146-103R	0.01 μ 39146-103R	0.01 μ 39146-103R
JUMP WIRE		J51	J51	J52	J52	J52
DEGAUSSING COIL		46G00-0059	46G00-0059	46G00-0063	46G00-0059	46G00-0063


NORMAL



PARTS	TYPE	HITACHI 20H14-0263	GOLDSTAR 20H14-2460	ORION 20H14-2660	mitsubishi 20H14-1860	CHUNGHWA 20H14-1061
R433		16K 1/4W 22225-163M	16K 1/4W 22225-163M	15K 1/4W 22225-153M	18K 1/4W 22225-183M	16K 1/4W 22225-163M
R434		5.1K 1/4W 22225-512M	5.1K 1/4W 22225-512M	5.1K 1/4W 22225-512M	5.6K 1/4W 22225-562M	4.7K 1/4W 22225-472M
R508		39K 1/4W 22225-393M	36K 1/4W 22225-363M	36K 1/4W 22225-363M	30K 1/4W 22225-303M	36K 1/4W 22225-363M
R805		75K 1/4W 22225-753M	68K 1/4W 22225-683M	75K 1/4W 22225-753M	110K 1/4W 22225-114M	75K 1/4W 22225-753M
R807		39K 1/8W 22215-393M	DELETE	DELETE	39K 1/8W 22215-393M	DELETE
R808		4.7K 1/8W 22215-472M	5.1K 1/8W 22215-512M	5.1K 1/8W 22215-512M	4.7K 1/8W 22215-472M	4.7K 1/8W 22215-472M
C823		0.01 μ 39146-103R	0.01 μ 39146-103R	0.01 μ 39146-103R	0.01 μ 39146-103R	0.01 μ 39146-103R
R803		47K 1/8W 22215-473M	120K 1/8W 22215-124M	120K 1/8W 22215-124M	120K 1/8W 22215-124M	120K 1/8W 22215-124M
R809		270 Ω 1/8W 22215-271M	82 Ω 1/8W 22215-820M	82 Ω 1/8W 22215-820M	82 Ω 1/8W 22215-820M	82 Ω 1/8W 22215-820M
C801		6800P 31115-682R	1000P 31115-102R	1000P 31115-102R	1000P 31115-102R	1000P 31115-102R
C807		10P 38196-100R	DELETE	DELETE	DELETE	DELETE



CRT / BOARD



CHUNTEX ELECTRONIC CO., LTD.			
MODEL :	1451C	PRT. NO :	11S31-039A
NAME :	MAIN	FILE NAME :	M39CWO1
REV :	C	DRAWN :	SUE YI CHEN
DATE :	1996/01/10	CHECK :	JEAN
UPDATE:	M.Y.LEE	UPDATE CHECK:	C.M.LENG







CHUNTEX ELECTRONIC CO., LTD.			
MODEL :	1451C	P/N. :	11S33-019A
NAME :	CRT B/D	FILE NAME :	14CC51B
REV :	B	DRAWN :	JEAN
DATE :	84-01-10	CHECK :	

MAIN BOARD

BRIGHTNESS

CONTRAST

V-CENTER


V-SIZE

H-PHASE




H-WIDTH



Q301



Q811




Q202

Q201

Q801


Q808

VR301
VR201
TP3



TP1

Q102
Q103



Q408

Q412

Q810
Q405

Q809

Q802

Q803

Q804

Q805

Q806

VR803

Q104

Q105
Q113
Q116

Q112

P401


Q411

Q410

Q407
GDS

P403
P402

D402 D401




D111

Q114
Q115

Q403
ECB
Q404


Q402

Q406



Q401
ECB


85V ADJ
VR101



Q111
Q501
GDS

P404

T401



VR501

Q503
Q502

IC501


F101

REV: B


V-LIN H-HOLD H-F/V
SIDE-PIN

H.V. ADJ

CRT BOARD



Q604



Q605


Q602

VR606


Q603

Q606

Q601



IC601



P601

P602

VR601
VR602
VR603

1451C